


TABELLA DI SCELTA PER COMANDO LAMPADE

Relè passo passo tipo PLS+ e monostabili VFR

	Potenza in W	Massimo numero di lampade		VFR 16 A
		PLS+ 16 A	PLS+ 32 A	
Glow lamps				
	15	200	266	120
	25	120	160	72
	40	75	102	45
	60	50	65	30
	75	40	52	24
	100	30	40	18
	150	20	26	12
	200	15	20	9
	300	9	12	6
	500	5		3
Fluorescent lamps with starter				
	18	81	100	50
	36	44	58	25
	40	38	53	23
	58	29	35	16
	65	26	34	13
Fluorescent lamps with ballast				
	18	103	132	17
	36	63	81	13
	40	40	77	12
	58	29	35	10
	65	17	28	7
Fluorescent lamps with duo circuit				
	2x18	82	110	50
	2x36	41	55	25
	2x40	35	50	23
	2x58	23	34	16
	2x65	12	23	13
Energy saving lamps				
	1x18	83	112	38
	1x36	46	61	30
	1x58	31	38	17
	2x18	40	56	19
	2x36	23	30	15
	2x58	14	19	8






	Potenza in W	Massimo numero di lampade		
		PLS+ 16 A	PLS+ 32A	VFR 16A
Halogen lamps 230 V				
	55	27	36	6
	90	17	22	4
	135	11	14	3
	185	8	10	2
High-pressure sodium-vapour lamps				
	70	15	18	10
	150	8	10	5
	250	4	6	3
	400	3	3	2
	1000	1	1	-
Low-pressure sodium-vapour lamps				
	55	25	29	6
	90	16	20	4
	135	11	12	3
	185	4	5	2
High-pressure mercury-vapour lamps				
	150	20	27	12
	250	12	16	7
	300	10	13	6
	400	7	10	4
	500	6	8	3
	1000	3	4	2
Low-pressure mercury-vapour lamps				
	20	116	160	72
	50	46	64	29
	75	31	42	20
	100	24	32	15
	150	15	21	10
	200	12	16	7
	300	7	10	5
	Fluorescent lamps with electronic ballast			
	1x18	83	112	38
	1x36	46	61	30
	1x58	31	38	17
	2x18	40	56	19
	2x36	23	30	15
	2x58	14	19	8

TABELLA DI SCELTA PER LAMPADE LED

Relè passo passo tipo PLS+ e monostabili VFR

	Application for (in W)	P [W] of the LED component	PLS+ 16A	PLS+ 32 A	VFR 16A
Switchable total power P (W) per contact path			200	250	200
LED E27 glow lamp shape					
	40	5.5	36	45	25
	40	6.0	33	42	23
	40	7.0	29	36	20
	60	9.0	22	28	16
	60	9.5	21	26	15
	60	10.0	20	25	14
	75	11.5	17	22	12
	75	13.0	15	19	11
	100	15.0	13	17	9
	100	18.0	11	14	8
LED E14 Candle-shaped bulb					
	25	3.0	67	83	40
	25	4.0	50	63	30
	40	6.0	33	42	20
	40	6.0	33	42	20
27/E14 Drop-shaped bulb					
	25	3.0	67	83	40
	25	4.0	50	63	30
	40	6.0	33	42	20
LED E27/E14 Reflectors					
	40	4.5	44	56	38
	50	5.5	36	45	22
	40	8.5	24	29	14
	40	9.5	21	26	13
	40	13.0	15	19	9
LED Low-voltage reflectors					
	20	3.4	59	74	35
	35	5.5	36	45	22
	35	6.5	31	38	18
	35	7.0	29	36	17
	50	8.0	25	31	15
LED High-voltage reflectors					
	35	3.5	57	71	34
	35	4.0	50	63	30
	50	4.5	44	56	27
	50	5.0	40	50	24
	50	5.4	37	46	22

	Application for (in W)	P [W] of the LED component	Number of LED components		
			PLS+ 16A	PLS+ 32 A	VFR 16A
Switchable total power P (W) per contact path			200	250	200
LEDTube 0.6 m fluorescent lamp with electronic ballast					
	18	10.5	19	24	11
LEDTube 1.2 m fluorescent lamp with electronic ballast					
	36	16.5	12	15	7
	36	18.0	11	14	7
	36	21.0	10	12	6
LEDTube 1.52 m fluorescent lamp with electronic ballast					
	18	10.5	19	24	11
	36	16.5	12	15	7
	36	18.0	11	14	7
	36	21.0	10	12	6
	58	22.0	9	11	5
	58	26.0	8	10	5
LEDTube 1.5 m with concentional/low-loss ballast					
	58	20.0	10	13	7
	58	23.0	9	11	5
	58	25.0	8	10	5
LEDTube 1.2m with concentional/low-loss ballast					
	36	16.0	13	16	8
	36	18.0	11	14	7
LEDTube 0.6m with concentional/low-loss ballast					
	18	8.0	25	31	15
	18	9.0	22	28	13