

TABELLA DI SCELTA PER COMANDO LAMPADE

Relè passo passo tipo PLS+

	Potenza in W	Massimo numero di lampade 16 A
Glow lamps		
	15	200
	25	120
	40	75
	60	50
	75	40
	100	30
	150	20
	200	15
	300	9
	500	5
Fluorescent lamps with starter		
	18	81
	36	44
	40	38
	58	29
	65	26
Fluorescent lamps with ballast		
	18	103
	36	63
	40	40
	58	29
	65	17
Fluorescent lamps with duo circuit		
	2x18	82
	2x36	41
	2x40	35
	2x58	23
	2x65	12
Energy saving lamps		
	1x18	83
	1x36	46
	1x58	31
	2x18	40
	2x36	23
	2x58	14






	Potenza in W	Massimo numero di lampade 16 A
Halogen lamps 230 V		
	55	27
	90	17
	135	11
	185	8
High-pressure sodium-vapour lamps		
	70	15
	150	8
	250	4
	400	3
	1000	1
Low-pressure sodium-vapour lamps		
	55	25
	90	16
	135	11
	185	4
High-pressure mercury-vapour lamps		
	150	20
	250	12
	300	10
	400	7
	500	6
	1000	3
Low-pressure mercury-vapour lamps		
	20	116
	50	46
	75	31
	100	24
	150	15
	200	12
	300	7
Fluorescent lamps with electronic ballast		
	1x18	83
	1x36	46
	1x58	31
	2x18	40
	2x36	23
	2x58	14

TABELLA DI SCELTA PER LAMPADE LED

Relè passo passo tipo PLS+

	Application for (in W)	P [W] of the LED component	Number of LED components PLSS+ 16 A
Switchable total power P (W) per contact path			200
LED E27 glow lamp shape			
	40	5.5	36
	40	6.0	33
	40	7.0	29
	60	9.0	22
	60	9.5	21
	60	10.0	20
	75	11.5	17
	75	13.0	15
	100	15.0	13
	100	18.0	11
LED E14 Candle-shaped bulb			
	25	3.0	67
	25	4.0	50
	40	6.0	33
	40	6.0	33
27/E14 Drop-shaped bulb			
	25	3.0	67
	25	4.0	50
	40	6.0	33
LED E27/E14 Reflectors			
	40	4.5	44
	50	5.5	36
	40	8.5	24
	40	9.5	21
	40	13.0	15
LED Low-voltage reflectors			
	20	3.4	59
	35	5.5	36
	35	6.5	31
	35	7.0	29
	50	8.0	25
LED High-voltage reflectors			
	35	3.5	57
	35	4.0	50
	50	4.5	44
	50	5.0	40
	50	5.4	37

	Application for (in W)	P [W] of the LED component	Number of LED components PLSS+ 16 A
Switchable total power P (W) per contact path			200
LEDTube 0.6 m fluorescent lamp with electronic ballast			
	18	10.5	19
LEDTube 1.2 m fluorescent lamp with electronic ballast			
	36	16.5	12
	36	18.0	11
	36	21.0	10
LEDTube 1.52 m fluorescent lamp with electronic ballast			
	18	10.5	19
	36	16.5	12
	36	18.0	11
	36	21.0	10
	58	22.0	9
	58	26.0	8
LEDTube 1.5 m with concnetional/low-loss ballast			
	58	20.0	10
	58	23.0	9
	58	25.0	8
LEDTube 1.2m with concnetional/low-loss ballast			
	36	16.0	13
	36	18.0	11
LEDTube 0.6m with concnetional/low-loss ballast			
	18	8.0	25
	18	9.0	22